



## Charge Vate

**Deka ChargeMate** combines a battery and charger into one unit to eliminate the need for remote charging equipment. Just connect the battery to its own internal charger, and plug it into any 15 amp 120 volt AC outlet for safe,

easy charging anywhere, at any time...for maximum convenience and flexibility.

Only **ChargeMate** features a **Deka** precision-constructed industrial battery, built with the world's most advanced computer-integrated manufacturing methods for the highest quality and best performance anywhere.

The specially matched auto start/stop charger gives the Deka ChargeMate maximum power, longer life and ease of operation.

Available in 12- and 24-volt, 150-425 ampere hour, the **Deka ChargeMate** fits all major sizes of pallet jacks.



 
 RECHARGE GUIDE:

 ESTIMATED HOURS OF OPERATION
 APPROX. HOURS TO RECHARGE

 1
 1.25 - 1.30

 2
 2.50 - 3.00

 3
 4.00 - 4.30

 4
 4.00 - 4.75

 5
 5.45 - 7.30

 6
 7.30 - 8.15

Recognized omponent WH17218	QUALITY SYSTEM CERTIFIED ISO 9001 ISO/TS 16949 ENVIRONMENTAL SYSTEM CERTIFIED ISO 14001
DECIFICATIONS*.	

SPECIFICATIONS*:										
LAYOUT BATTERY	A.H. CAPACITY	K.W.H. CAP.	A.C.	DIMENSIONS (INCHES)			APPROX.			
NUMBER	TYPE	6 HR. RATE	6 HR. RATE	R. RATE SUPPLY	LENGTH	WIDTH	HEIGHT	WEIGHT (lbs.)		
IST1061	6-D75-11	375	4.37	120 Volts	31¼	7¾	23¼	505		
IST1061	6-D85-11	425	4.94	120 Volts	31¼	7¾	23¼	526		
IST3167	12-D75-5	150	3.50	120 Volts	24¼	<b>8</b> 5⁄16	23¼	450		
IST3167	12-D85-5	170	3.95	120 Volts	24¼	<b>8</b> 5⁄16	23¼	470		
IST3416	12-D75-5	150	3.50	120 Volts	331/16	<b>6</b> ½6	23¼	450		
IST3416	12-D85-5	170	3.95	120 Volts	331/16	67/16	23¼	470		
IST3415	12-D75-7	225	5.24	120 Volts	30½	8%6	23¼	581		
IST3415	12-D85-7	255	5.92	120 Volts	30½	8%6	23¼	607		
IST3163	12-D75-11	375	8.74	120 Volts	31%	12%	23¼	925		
IST3163	12-D85-11	425	9.88	120 Volts	31%	12%	231/4	958		

<sup>\*</sup> Additional models are available upon request. Contact factory for specifications and pricing.



DISTRIBUTED BY:

Lyon Station, PA 19536-0147 • Phone: 610-682-6361 • Fax: 610-682-4212

Order Department Hotline: 610-682-3260

www.dekabatteries.com • e-mail: epmmotve@eastpenn-deka.com